Active Harmonic Filter, Power Factor Correction, Phases Unbalance

30 A / Wall

The combined systems of the AXG series have a sophisticated power quality control capability.

AXG collects the current trends in real time, sending them to an internal control circuit, via n. 3 CTs installed on the loading side.

Through integrated FPGA technology, the fundamental components of the currents, the harmonic components, the reactive currents and the components responsible for the imbalance are extracted; the needed currents for compensation and the compensation currents emitted by the AXG system are compared, and the difference is calculated.

In order to allow the IGTB inverter to be able to inject the necessary currents into the electrical network, input signals are emitted to the driving circuit, so as to achieve closed-loop control and complete the compensation function, both in terms of filtering and of power factor correction.

The operating modes operate according to the priority principle (selectable), to be chosen between Active Filter (AHF), Power Factor Correction (PFC) and Phase Balancing (UNBALANCE)

AHF, Active Harmonic Filter mode

AXG is able to filter harmonic currents (THDi) up to the 50th order and significantly reduce the THDv components. Applicable in any condition in both the industrial and civil sectors, they represent the ideal solution for the treatment of non-linear three-phase loads, with or without neutral

PFC, Power Factor Correction mode

AXG, thanks to its electronic operation, is able to operate where a traditional power factor correction system could not do the same with the appropriate reliability over time.

For example, all applications - mainly in heavy industries - with prohibitive harmonic contents - both current and voltage - also for power factor correction systems with detuning inductors.



